



Product Overview

The AX-DAOM converts a 0-10Vdc or 2-10Vdc input signal to two 0-10Vdc or 2-10Vdc output signals, with an adjustable deadband. Either output can be inverted via a jumper. The unit is powered from 24Vac/dc and has Rising Clamp Screw Terminals. The AX-DAOM is designed to mount onto TS35 section DIN rail.

Features

- 2 x 0-10Vdc or 2-10Vdc outputs
- 1 x 0-10Vdc or 2-10Vdc input
- Individual inversion of outputs
- 24Vac/dc supply

- Adjustable deadband
- High quality Rising Clamp Terminals
- DIN rail mounting

Product Specifications

Input Signal
Output Signal
Power Supply
Terminals
LED Indicators
Ambient Temperature Range
Dimensions
Country of Origin

0-10Vdc or 2-10Vdc 2 x 0-10Vdc or 2-10Vdc @ max load 10mA each 24Vac/dc ±15% 40mA max @ 24Vdc Rising Clamp for 0.5-2.5mm² cable Flashes to indicate operation 0 to 50°C 78(W) x 92.5(H) x 50(D)mm (approx) United Kingdom

Order Codes

AX-DAOM

Dual Analogue Output Module


© Copyright Annicom. All Rights Reserved

Annicom Ltd Unit 21, Highview, Bordon, Hampshire. GU35 0AX Tel: +44 (0)1420 487788 Fax: +44 (0)1420 487799 Email: sales@annicom.com Website: www.annicom.com



Installation

The AX-DAOM should be installed by a suitably qualified technician in conjunction with any guidelines for the equipment it is to be connected to and any local regulations. Field wiring should be installed to satisfy the requirements set out by the manufacturer of the equipment that the module is being connected to.



Configuration

Potentiometers Cut-off points can be adjusted to overlap if required. LED flashes faster when this adjustment is made.

Commissioning

The units come factory fitted with the deadband approximately between 4 and 6 volts if you require a different setting. Adjust the relevant potentiometer as required.

0 selects 0-10V input and outputs

2 selects 2-10V input and outputs (if inputs are less than 1V both outputs will be 0V - fault condition).

Every effort has been taken in the production of this data sheet to ensure accuracy. Axio do not accept responsibility for any damage, expense, injury, loss or consequential loss resulting from any errors or omissions. Axio has a policy of continuous improvement and reserves the right to change this specification without notice.